

AR3 SERIES INSTALLATION INSTRUCTIONS HIGH VOLTAGE – 347-480V INPUT

Materials Required by Contractor:

- 90°C rated supply conductors

Box Contains:

- 1 AR3 or AR3-HO fixture
- 1 Mounting Yoke
- 1 Screw to mount fixture to yoke



Before Starting Work:

- Ensure that all electrical connections are not live! Take all steps necessary to make sure that electrical connections will not become live accidentally during installation. Installation is to be completed by a qualified electrician only.
- Ensure input voltage is correct per ETL label on luminaire.

Installation Steps:

1. Remove luminaire from box. Install lower portion of mounting yoke onto luminaire using hex-bolt provided. When installing mounting yoke, adjust to desired mounting angle. Route electrical cord through mounting yoke.
2. Hold luminaire near mounting arm. Make electrical connections. Use 90°C rated supply conductors only.

Brown = Hot
Brown = Hot
Green = Ground

3. Slide fixture onto light pole. Tighten mounting yoke screws to secure light fixture to light pole.

Note: The AR3 and AR3-HO series are not intended to be used as up-lights.